



Standard Horizon GX1500E/ GX3000E / VM3500E /GX1100E\*

**MMSI/ATIS QUOTE**

**June 2009**

To change or input the MMSI and/or ATIS number and enable it in your radio we charge £32 including VAT and return carriage.

Please include a letter detailing MMSI/ATIS number or copy of OFCOM letter with new MMSI/ATIS number.

Proof of purchase is not necessary but if easily available can be enclosed.

Please ensure you include a daytime phone number with your letter, as we use TNT signed next day, for delivery.

As for payment, an invoice is normally posted, for payment before dispatch of goods.

If dispatching the radio by post or courier service, please ensure that it is correctly packed and protected. The original shipping carton with the internal protection cutouts is ideal.

It is not necessary to send any manuals, cables or accessories with the radio other than the microphone

Please send the radio with requisite paperwork to the following address.

**FAO SERVICE DEPARTMENT**

YAESU U.K. LTD  
Unit 12, Sun Valley Business Park,  
Winnall Close, Winchester  
SO23 0LB  
United Kingdom  
Phone: +44-1962-866667  
Fax: +44-1962-856801

**Notes on ATIS Mode**

To enable ATIS to be used on our GX-1500E/3000E/VM3500E we have converted the Canadian Channel mode to ATIS mode. To operate in ATIS mode you must select CAN mode on the radio. To change mode from International (INT) to Canadian (CAN), press and hold the 16/9 key and then press the WX key. Each press of the WX key will change the mode from INT to USA to CAN to INT etc. Select CAN for ATIS mode. You will notice ATIS on the channel description when in this mode.

Note also that Scanning and Dual Watch are not permitted in ATIS Mode and are disabled. DSC should not be used in inland waterways.

\*GX1100E has ATIS mode enabled as a user selectable menu option, so the user can enter their ATIS number and enable/disable ATIS mode as required.